

GFCI

20 AMP LINE & LOAD SIDE USER ATTACHABLE IN-LINE GFCI

Tower's 20 Amp line & load side user attachable in-line GFCI



30396500-08

Model 30396500-08 manual reset in-line GFCI can be added to or replace a GFCI plug on any power tool or equipment power cord.

The user can wire to both the line and load side. Hardware is provided to allow wiring to cord gauge 12/3 SJTW.

The bright "Red" light indicates when the power is "ON". The TEST and RESET buttons allow for periodic testing.

FEATURES

MODEL 30396500-08

- Compatible with 15 and 20 amp U-ground outlets and plugs, 2 or 3 wire
- Trip level 4-6 mA
- UL and CUL listed
- Manual reset
- Rated for indoor and outdoor use

SIMILAR MODELS

**MODEL 30338023
USER ATTACHABLE IN-
LINE GFCI, 15 AMP**

SPECIFICATIONS

- Class "A" people protection GFCI
- Rated for 125 volt, 20 amp use
- 2500 watts, 60 Hz
- LED Power "ON" indicator
- Open neutral and ground neutral protection
- Operating temperature range -35 degree C to 66 degree C
- Impact resistant case